

# Home Complete

SKU: 470145    MAP: \$999.99

## FEATURES

- Boosts all available networks speeds for enhanced cell signal coverage
- Offers an ideal solution for small business owners
- Supports multiple cellular devices and users simultaneously
- Works on all major US carriers; Verizon, AT&T, T-Mobile, Sprint, UScellular, and more




- 5G READY
- MAX COVERAGE
- UP TO +72 dB GAIN
- MULTI-USER WIRELESS BOOSTER

## About

The weBoost **Home Complete** is the best-in-class booster for those who like to get it done. Everything needed for installation in a residential or commercial building is included. Once installed, this powerful booster improves cell signal on all U.S. carrier networks, including Verizon, AT&T, T-Mobile, and more. Its contemporary design and 5G-ready coverage ensure it will work for the next decade and beyond. Like all weBoost solutions, it comes with an installation guide, a 2-year manufacturer's warranty, and a 30-day money-back guarantee.

## Kit Includes



## Coverage Area


IF THE OUTSIDE CELL SIGNAL IS:	→	YOUR BOOSTED CELL SIGNAL MAY COVER:
Strong	→	Max Coverage
Good	→	Multiple Rooms
Weak	→	Single Room
None	→	None

## Specifications

SKU NUMBER	470145 <sup>†</sup>
FREQUENCIES	Band 12/17    700 MHz Band 13    700 MHz Band 5    850 MHz Band 4    1700/2100 MHz Band 25/2    1900 MHz
MAX GAIN	72 dB
IMPEDANCE	75 Ohm
POWER	110-240V AC, 50-60 Hz, 20 W
CONNECTORS	F-Female
BOOSTER DIMENSIONS	8.25 x 6 x 2.4 in
BOOSTER WEIGHT	1.55 lbs

<sup>†</sup> **WARNING:** This product can expose you to chemicals including Nickel, which is known to the State of California to cause cancer, and Bisphenol A, which is known to the State of California to cause birth defects or other reproductive harm. For more information go to [www.P65Warnings.ca.gov](http://www.P65Warnings.ca.gov)

## How It Works



- 1 **Receives signal:** The outside antenna reaches out to access the existing strong outdoor cell signal and delivers it inside to the booster.
- 2 **Boost signal:** The booster receives the signal, amplifies it, and serves as a relay between your phone and the nearest cell tower.
- 3 **Broadcasts signal:** Your devices get a stronger signal, and calls and data are fed through the booster back to the network.

## Available Accessories



Inside Panel Antenna with mount (314444)



Outside Directional Antenna with mount (314445)



75' RG-11 Extension Cable with F Male Connectors (951175)



Splitters 75 Ohm (850034, 850035, 850036)



Lightning Surge Protector 75 Ohm (859992)

## Support



2-Year Warranty from Purchase.



UPC

